

AddOn Computer
34A Mauchly
Irvine, Ca 92618

Office: 949.861.2800
Fax: 949.861.2812
www.addoncomputer.com



MEDIA CONVERTERS - MEMORY UPGRADES
BATTERIES - NETWORKING TRANSCEIVERS

10/100/1000M TX-XX Managed

1000BASE-TX To 1000BASE-FX
Gigabit Ethernet Managed Media Converter



Features

Interface/Ports:	1 x RJ-45, 1 X SC, ST or SFP
Connectivity:	Twisted Pair, Fiber
Connectivity Media:	10/100/1000Base-T Twisted Pair 1000Base-XX (50/125 μ m, 62.5/125 μ m MMF) (9/125 μ m SMF)
Distance Supported:	550m, 20km
Wavelength:	850nm, 1310nm, 1550nm
Network Technology:	10/100/1000Base-T 1000Base-XX (SX,LX,BX)
Status Indicators:	Power Copper Link Fiber Link Copper Receive activity Fiber Receive activity
Input Voltage:	120V
Input Current:	1A
Temperature:	32°F (0°C) ~ 122°F (50°C)
Humidity:	5 ~ 90% Non-condensing

Product Description

The AddOn line of products is a complete offering of Managed Fiber Media Converter. 10/100/1000M TX-XX Managed Media Converter Functions including variety of data rate, SM/MM, single fiber and double fiber etc. with simple set-up. Real time remote manageable fiber media converters. AddOn Media Converters and Network Interface Cards are 100% compliant for all of our networking needs.

ADD-MGMC-SX-5SC

Managed Media Converter 1000BSX
10/100/1000M 850NM MMF SC 550m

ADD-MGMC-LX-2SC

Managed Media Converter 1000BLX
10/100/1000M 1310NM SMF SC 20km

ADD-MGMC-BX-USC

Managed Media Converter 1000BXU
1310/1550NM BiDi SMF SC 20km Reach

ADD-MGMC-BX-DSC

Managed Media Converter 1000BXD
1550/1310NM BiDi SMF SC 20km Reach

ADD-MGMC-SFP*

Managed Media Converter 1000M SFP
10/100/1000M with open SFP slot

ADD-MGMC-SX-5ST

Managed Media Converter 1000BSX
10/100/1000M 850NM MMF ST 550m

ADD-MGMC-LX-2ST

Managed Media Converter 1000BLX
10/100/1000M 1310NM SMF ST 20km

ADD-MGMC-BX-UST

Managed Media Converter 1000BXU
1310/1550NM BiDi SMF ST 20km Reach

ADD-MGMC-BX-DST

Managed Media Converter 1000BXD
1550/1310NM BiDi SMF ST 20km Reach

*For complete list of SFP/XFP module
please visit www.addoncomputer.com